

Tel.: +86 20 39388220
Fax: +86 20 31072811

Web: <http://www.rhaudio.com/>
Email: info@rh-audio.net

PA Sound System Two Channel 100V Amplifier



[RH-AUDIO](#) PA Sound System Two Channel 100V Amplifier are designed for background music/paging and public address system installations, these units are exceptional values, loaded with features, and are easy to install in variety of system designs.

The 2-channel power amplifier features two channels for two channel speaker selector individually, with either 70/100-volt or 4 to 16 ohms(Ω) output loads.

And features complete protection is provided for output short circuit, overload, high temperature, peak current limiters.

The characteristics of [sound power amplifier](#):

- ※ 2U aluminium panel.
- ※ With 2 channel speaker selector.
- ※ 2 line inputs.
- ※ Individual volume controller for each zone.
- ※ 70V, 100V and 4~16 Ω outputs.
- ※ Output short circuit, overload, high temperature protection.

The specifications of [2 channel power amp](#):

Model	RH28206W	RH28212W	RH28225W	RH28235W
Rated Power	2*60W	2*120W	2*250W	2*350W
Output	4-16 ohms(Ω), 70V/100V			
Input Sensitivity	10K Ω 260~470mV , unbalanced			
Aux. Output	0.775V (0 dBV)			
Frequency Response	60 Hz ~ 15k Hz (\pm 3 dB)			
THD	<0.5% at 1kHz			
S/N	\geq 85 dB			
Controls	two volume controls, one power control			



Guangzhou Xinghongde Electronics Technology Co., Ltd.

Tel.: +86 20 39388220

Web: <http://www.rhaudiopa.com/>

Fax: +86 20 31072811

Email: info@rh-audio.net

Cooling	DC 12V FAN			
Indicator	'POWER','CLIP','SIGNAL','PROT','TEMP'			
Protection	AC FUSE×6A	AC FUSE×8A	AC FUSE×10A	AC FUSE×12A
Power Cable	(3×1.5 mm ²)×1.5M (standard)			
Power Supply	Optional			
Power Consumption	185W	310W	620W	830W
Dimension	89(H)×483(W)×366(D) mm			
Net Weight	10.5 Kg	11.5 Kg	13.8 Kg	14.5 Kg

