

Tel.: +86 20 39388220  
Fax: +86 20 31072811

Web: <http://www.rhaudiopa.com/>  
Email: [info@rh-audio.net](mailto:info@rh-audio.net)

### Digital FM/AM/DAB+ Radio Tuner RH650FRD

- ※ Incorporates a digital module for precise reception of AM,FM,RDS,DAB and DAB+ signals.
- ※ Enjoys a USB port on front panel allowing to play USB disk.
- ※ An AUX input allowing to connect additional audio source.
- ※ Bluetooth connectivity is optional.
- ※ A rear panel RS232 serial port is equipped.
- ※ 1U design for installation in standard equipment racks or on desk,removable rack mounting brackets.

### Descriptions of Digital FM/AM/DAB+ Radio Tuner RH650FRD

The **RH-AUDIO** 1U Digital FM/AM/DAB+ Radio Tuner RH650FRD is an ideal as a background music source in a sound system of all sizes by providing broadcast program material, it incorporates a digital module for precise reception of AM, FM, RDS, DAB and DAB+ signals.

Moreover this player enjoys a USB port on front panel allowing to play USB disk, also an AUX input allowing to connect an additional audio source such as cd player, computer, mobile phone etc. Bluetooth connectivity is optional.

User can operate this device by pushing the buttons on its front panel or using its remote control.

### Specifications of Digital FM/AM/DAB+ Radio Tuner RH650FRD

Model	RH650FRD
Media source	AM,FM,RDS,DAB,DAB+,USB,BT
Audio output	500mVrms
Output impedance	1K ohm
AM SECTION	
Frequency range	522-1620 KHz STEPS 9KHz
Sensitivity	16dB
S/N	40dB
Distortion	0.30%
Frequency Response	80Hz-4KHz
FM SECTION	



Guangzhou Xinghongde Electronics Technology Co.,Ltd.

Tel.: +86 20 39388220

Web: <http://www.rhaudiopa.com/>

Fax: +86 20 31072811

Email: [info@rh-audio.net](mailto:info@rh-audio.net)

Frequency range	87.5-108MHz STEPS 50KHz
Sensitivity	20dB
S/N	40dB
Distortion	0.20%
Frequency Response	20Hz-20KHz
Antenna Impedance	75 Ohm
Net Weight	2.26kg
Gross Weight	3.5kg



Guangzhou Xinghongde Electronics Technology Co.,Ltd.