

Tel.: +86 20 39388220
Fax: +86 20 31072811

Web: <http://www.rhaudiopa.com/>
Email: info@rh-audio.net

10 Zone Monitor Panel RH2812M



The PA System 10 Zone [Fire Alarm Interface Panel](#) RH2812M is designed to provide aural monitoring for the outputs of up to 10 zones audio source with 70 and 100-volt line outputs, it is helpful for pa system in control room to monitor the outside program status. It includes a 5" monitor speaker, a volume control, 6 LED meters, and a 11-position (OFF and 10 channels) selector switch. The variable intensity LED meter on the front panel will indicate the signal level (0dB, 2dB, 4dB, 6dB, 8dB, 10dB) for the selected channel.

The Features of [Fire Alarm System Panel](#)

- ※ Built-in full-range speaker 5W/8 Ohm with volume control.
- ※ Connecting to the amplifiers or multi-zone speaker selector to monitor the program status.
- ※ Monitors up to 10 speaker zones by using the built-in speaker.
- ※ 6 LED level meters visually indicates the channel signal level.

The Specification of [RH-AUDIO](#) 10 Zone Monitor Panel

Model	RH2812M
Line Input	70V/100V, audio signal
Channels	'CH1~CH10'
Monitor Speaker	'HiFi' full range, 5W
Power Cable	(3×0.75 mm ²)×1.5M
Power	AC 220V±10% 50-60Hz
Power Consumption	10~15W
Size	89(H)×483(W)×350(D) mm
Carton Size	185(H)×520(W)×435(D) mm
Net Weight	6.34kg
Gross Weight	7.88kg



Guangzhou Xinghongde Electronics Technology Co., Ltd.