

Tel.: +86 20 39388220  
Fax: +86 20 31072811

Web: <http://www.rhaudiopa.com/>  
Email: [info@rh-audio.net](mailto:info@rh-audio.net)

## WIFI/USB/BT Portable Mixing Amplifier

Features of WIFI/USB/BT Portable Mixing Amplifier:

- ※ Built-in WiFi wireless music streaming receiver,Bluetooth receiver and USB player.
- ※ Connect with your smart device via the free app.
- ※ Support AIRPLQY/DLAN/QPLAY.
- ※ One RJ45 port available for the point where the WiFi signal is weaker.
- ※ 70/100-volt and 4/8 ohms( $\Omega$ ) output loads.
- ※ SMT circuit boards with highly stable performance.
- ※ Powerful amplifier tubes.
- ※ Three microphone sockets support unbalanced 6.35mm jack.
- ※ Mic 1 has priority over the inputs with 0~30dB dB attenuation.
- ※ High-definition display for the working status of playing programme.
- ※ Individual volume controller for inputs,and master volume controller for all.
- ※ BASS and TREBLE tone controllers.
- ※ Complete protection is provided for output short circuit, overload, high temperature,peak current limiters.

### Description Specification

#### Description of [WIFI/USB/BT Portable Mixing Amplifier](#):

This [RH-AUDIO](#) WIFI/USB/BT Portable Mixing Amplifier is designed as convenient solution for small to medium PA installations with USB player,Bluetooth and WIFI receivers in a compact housing.

Its outstanding feature of WiFi wireless music streaming receiver,supports connection with your smart device via a free APP, one RJ45 port is available on the rear panel as a backup for the point where the WiFi signal is weaker.

Equipped with step-up transformer to be best suitable for any 70-volt or 100-volt line public address system, in the same time 4 & 8 ohms( $\Omega$ ) output loads are also provided.

Three balanced XLR microphone inputs are fixed on the rear,via the button "VOICE PRIORITY" the MIC1 can be set with priority over the other inputs,moreover the MIC1 has another port of 6.35mm socket on front panel.

Level controllers include volume controller for inputs,master volume controller for all,BASS and TREBLE tone controllers.

Complete protection is provided for over temperature, over voltage, over load and short circuit speaker line conditions.



Guangzhou Xinghongde Electronics Technology Co.,Ltd.

Tel.: +86 20 39388220

Web: <http://www.rhaudiopa.com/>

Fax: +86 20 31072811

Email: [info@rh-audio.net](mailto:info@rh-audio.net)

### Specifications of WIFI/USB/BT Portable Mixing Amplifier

Model	RH60WIFI
Rated Power	60W
Output Terminals	Low impedance: 4/8ohms ( $\Omega$ ), Voltage line:70V( 81.7 ohms), 100V(166.7ohms)
MIC Input	10Kohms( $\Omega$ ) 9.2 mv,unbalanced
LINE Input	LINE: 10K ohms( $\Omega$ ) 260 mv,unbalanced
Frequency Response	30Hz ~ 15k Hz ( $\pm$ 3 dB)
THD	< 0.5% at 1kHz,1/3 rated power
S/N	Line:85 dB , MIC:> 80 dB
Tone	BASS:100 Hz ( $\pm$ 10dB) , TREBLE:10k Hz ( $\pm$ 10dB)
Protection	AC fuse,short circuit,overload,high temperature
Power Cable	(3 $\times$ 0.5 mm ) $\times$ 1.5M (standard)
Power Supply	AC 220V $\pm$ 10% 50- 60Hz (Optional)
Power Consumption	84W
Net Weight	5.00kg
Dimension	75(H) $\times$ 280(W) $\times$ 240(D)mm



Guangzhou Xinghongde Electronics Technology Co.,Ltd.